



298.00 EUR

incl. 19% VAT, plus [shipping](#)

### 500W DC ATX P4 Power Supply (9-18VDC)

Now you can power every PC in your car. 500W power and Pentium-4 connector are giving you all possibilities !  
The ATX connector has 24 pins. Along with the power supply there is a 24pol to 20pol ATX adapter included.

|                              |                                                                   |
|------------------------------|-------------------------------------------------------------------|
| Dimensions                   | 150mm[W] × 170mm[L] × 86mm[H] Standard ATX PS/2 size              |
| Weight                       | 2.67 kgs                                                          |
| Input Voltage Range          | 9 - 18VDC                                                         |
| Output Power maximum         | 500W                                                              |
| Output Power maximum (rails) | +3.3V : 35A<br>+5.0V : 60A<br>+12.0V : 35A                        |
| Remote sensing               | +5V and +3.3V                                                     |
| Over Power Protection        | Load over 130%±10% of max. output power : shutdown                |
| Over Voltage Protection      | +5V, +12V & +3.3V Auto-recovery                                   |
| Short Circuit Protection     | Main outputs shutdown and latch off                               |
| Over Temperature Protection  | OTP Level is set at 110°C                                         |
| Operating Temperature        | -20°C ~ +70°C                                                     |
| Storage Temperature          | -40°C~+80°C                                                       |
| Cooling                      | Build-in One 80x80x25mm Ball Bearing Fan with max. air flow 42CFM |